

BS CHARGER

Automatic Battery Charger Charge & Maintain



BA10



SECURE CHARGE
Seasonal Battery Maintenance



SPEED CHARGE
Rapid Charge Function



VOLTAGE SWITCH
Voltage Output Selection

BA10

AUTOMATIC

BATTERY CHARGERS

6V/12V - 1000mA Automatic Battery Charger Charger & Maintainer



SPECIFICATIONS	
PART NUMBER	BA 10
TYPE	Automatic
INPUT VOLTAGE RANGE	100-240Vac
INPUT FREQUENCY	50/60Hz
OUTPUT	1000mA at 6V or 12V
CHARGING OUTPUT CONTROL CHARACTERISTICS	
Battery Condition Check-->Bulk Charge-->Float Charge	
Charging Output Control for:	6V 12V
Bulk Charging Start when Battery Voltage is above:	4.4V 8.8V
APPROVALS	CE, UL/cUL, Mzs, As

“Ideal for all VRLA & Conventional type lead acid batteries as in vehicles, marine, utility appliance, home appliance, workshops, farm machinery, and other appliances”

FEATURES

Automatic Charge

Automatically stops charging when the battery is fully charged. No need to unplug, charger never overcharge the battery

Automatic Maintenance

When the battery is charged to "full" state, the charger automatically switches to maintain the battery. It will monitor the battery voltage and continue to peak performance to the battery

“Short circuit & Reverse polarity” Protection

Prevents from sparking due to the reserve connection or short circuit. The charger will automatically turn off to prevent any damage



6V/12V Voltage Output Selection

BA10's Voltage Switch allows to charge different battery Types & Sizes with the same charger

Other Features

- Three level charge control
- Internal over heat protection
- Corrosion-resistant output connectors
- Output clips and ring terminals provided

L.E.D CHARGE INDICATION	
LED Status	■ Power ■ Charging ■ Full / ■ Fault
A.C power connected, battery disconnected	■
Bulk Charging	■ ■
Level 1 charging	■ ■
Level 2,3 charging	■ ■ ■
Battery reverse polarity protection	■ ■



Perfect for the Charging and Maintaining of the following applications:



BS
CHARGER